

XAW-P


The XAWP range of pendant control stations is suitable for all kinds of industry, especially those where an explosive atmosphere may be present. This range is certified ATEX II 2 GD. Primarily used on cranes. Our pendant control station is available with 2, 4, 6, 8 pushbuttons and offers a variety of simple and complex design features including 12 or 16 push-button models.

Specifications










Material	Metal, Rubber and GRP
IP Rating	IP65
Temperature	20°C to +60°C (without lighting functions) -20°C to +50°C (with lighting functions)
Approvals	INERIS 03ATEX0122
Standards	Cenelec EN50014, EN50018, EN50019, EN50028, EN500281-1-1
Ex-Code	II 2 GD - Ex ed IIC / Ex emd IIC
Mounting	Assembly of components only by TECHNOR
Cable entry capacity	for Ø10 to Ø22 mm cable
Connection	Screw clamp terminals From 1 x 0,5 mm ² cable to 2 x 1,5 mm ² cable (with or without ferrule)
Availability	Standard version available on catalogue Special version available on request












Dimensions









Stations







Fitted with interchangeable booted operators and cable boot suitable for Ø10 to Ø22mm				
Number of way	Function	Contact blocks mounted on each way	Reference	Weight Kg
2		 1 N/O	XAWP271	0,940
		 1 N/C + 1 N/O	XAWP281	1,000
4		 1 N/O	XAWP471	1,290
		 1 N/C + 1 N/O	XAWP481	1,400
6		 1 N/O	XAWP671	1,650
		 1 N/C + 1 N/O	XAWP681	1,800

Fitted with interchangeable booted pushbutton, operators with start and emergency stop functions. With labels in yellow blank and cable boot suitable for Ø10 to Ø22mm cable.					
	Number of way	Function	Contact blocks mounted on each way	Reference	Weight Kg
Fitted with interchangeable booted pushbutton, operators with start and emergency stop functions. With labels in yellow blank and cable boot suitable for Ø10 to Ø22mm cable	4		 1 N/O For Direction and Start Functions	XAWP472	1,320
			 1 N/C + 1 N/O For All Functions	XAWP482	1,380
	6		 1 N/O For Direction and Start Functions	XAWP672	1,650
			 1 N/C + 1 N/O For All Functions	XAWP682	1,690
	8		 1 N/O For Direction and Start Functions	XAWP872	2,000
			 1 N/C + 1 N/O For All Functions	XAWP882	2,250

Double step pushbutton stations

Fitted with “double” step mechanism on each pushbutton. Legend plate 30x40mm black or white symbols on white or black background. Cable boot suitable for Ø10 to Ø22mm				
Number of way	Function	Contact blocks	Reference	Weight Kg
2			XAWP2271	1,000
4			XAWP4271	1,400
6			XAWP6271	1,800

Double step pushbutton stations

Fitted with “double” step mechanism on each indicator. Illuminated or not start pushbutton label I, red Ø40 Mushroom head latching to release, yellow blank label, cable boot suitable for Ø10 to Ø22mm				
Number of way	Function	Contact blocks	Reference	Weight Kg
4			XAWP4272 with standard START pushbutton XAWP4373 with illuminated START pushbutton	1,350
6			XAWP6272 with standard START pushbutton XAWP6373 with illuminated START pushbutton	1,800
8			XAWP8272 with standard START pushbutton XAWP8373 with illuminated START pushbutton	2,250

Accessories and spare parts

Type	Function	Reference
Empty pendant control station for mounting exclusively by TECHNOR	02 buttons	XAWP029
	04 buttons	XAWP049
	06 buttons	XAWP069
	08 buttons	XAWP089
	12 buttons	XAWP069D
	16 buttons	XAWP089D
Slow break contact block	N/O	ZBWE101
	N/C	ZBWE102
Complete booted pushbutton operator	White (W)	XAWP9411
	Black (B)	XAWP9412
	Green (G)	XAWP9413
	Red (R)	XAWP9414
Selector switches (Stayput)	2 pos. Black+NO	XBW5AD21
	3 pos. Black+2NO	XBW5AD33
Illuminator pushbutton "Start"	Green (G)+NO	XLW5AV033
Pilot light + head (-24V to 415V AC-DC)	White	XLW5AV013
	Green	XLW5AV033
	Red	XLW5AV043
	Yellow	XLW5AV053
Blank plug		XLW5AV063
		XAWZ3
Double step push-buttons (use only with ZBWE101 contact blocks)	White (W)	XAWP9421
	Black (B)	XAWP9422
Emergency Mushroom head (Ø40)	Red+NC	ZA2BS54 + ZBWE102
Emergency Mushroom head (Ø30)	Red+NC	ZA2BS44 + ZBWE102

ARROW for Double step pushbutton

UP	ZBWE4953
DOWN	ZBWE2956
RIGHT	ZBWE4903
LEFT	ZBWE2906
FORWARD	ZBWE4965
REVERSE	ZBWE2968

ARROW for Single step pushbutton

UP	ZBWE4951
DOWN	ZBWE2954
RIGHT	ZBWE4901
LEFT	ZBWE2904
FORWARD	ZBWE4963
REVERSE	ZBWE2966
FAST UP	ZBWE4952
FAST DOWN	ZBWE2955
FAST RIGHT	ZBWE4902
FAST LEFT	ZBWE2905
FAST FORWARD	ZBWE4964
FAST REVERSE	ZBWE2967
I	ZBWE4980
O	ZBWE2931
O - I	ZBWE2178
I - II	ZBWE2179
I - O - II	ZBWE2186
EMERGENCY STOP	ZBWE2330



XAWP9411



ZBWE101



XLW5AV033